

H7 Family Trims

OPEN TRIMS

328

Open Splay Trim

Lamps: R30, BR30, PAR30*
328=White Open Splay Trim
O.D = 7 3/4" (197mm)

Used In:


H7ICT, H7ICAT, H7RICT, H7RICAT
H27ICT, H27ICAT, H27RICT
H27T, H27RT

H7T-328 75W PAR30FL 1100 Lumens				H7T-328 75W R30FL 900 Lumens			
Dia	FC	Work Plane		FC	Dia		
3'0"	81	5'6"		15	6'0"		
4'0"	58	6'6"		11	7'0"		
5'0"	38	8'0"		7	8'0"		
6'0"	24	10'0"		4	10'0"		
7'0"	17	12'0"		3	12'0"		

Based on Bare Lamp Data

Work Plane is 2 1/2 ft above floor

Dia of circle is 50% of max footcandles directly under fixture



328 Splay

401

Open Trim

Lamps: R40*
401AL=Aluminum Finish
Open Trim
401P=White Open Trim
401PB=Polished Brass Open Trim
O.D = 8" (203mm)


Used In:

H7T, H7RT
H7UICAT, H7UICAT

H7T-401 75W R40 SP 1900 Lumens				H7T-401 75W R40 FL 1900 Lumens			
Dia	FC	Work Plane		FC	Dia		
2'0"	270	4'6"		50	4'6"		
2'6"	129	6'6"		24	6'6"		
3'0"	76	8'6"		14	8'6"		
4'0"	50	10'6"		9	10'6"		
5'0"	35	12'6"		7	12'6"		
6'0"	26	14'6"		5	14'6"		

Work Plane is 2 1/2 ft above floor

Dia of circle is 50% of max footcandles directly under fixture



401 Open

428

Open Splay Trim

Lamps: R40*
428P=White Open Splay Trim
O.D = 7 3/4" (197mm)


Used In:

H7T, H7RT
H7UICAT, H7UICAT

H7T-428 75W R40 SP 1900 Lumens				H7T-428 75W R40 FL 1900 Lumens			
Dia	FC	Work Plane		FC	Dia		
2'0"	270	4'6"		50	4'6"		
2'6"	129	6'6"		24	6'6"		
3'0"	76	8'6"		14	8'6"		
4'0"	50	10'6"		9	10'6"		
5'0"	35	12'6"		7	12'6"		
6'0"	26	14'6"		5	14'6"		

Work Plane is 2 1/2 ft above floor

Dia of circle is 50% of max footcandles directly under fixture



428 Open

* Lamp Wattage and type vary with Housings.

Refer to individual housing sheets for specific wattage ratings