

# Enjoy performance and value

## Cost savings

Compared to fluorescent, EvoKit LED retrofit kits are energy efficient and dimmable to help reduce maintenance and operating costs. Connected lighting options help to further optimize lighting-related energy expenses. Additionally, EvoKit is a more cost-effective solution than complete luminaire renovations because of its low price and reduced project scrap, and can be installed in less than five minutes without tools or the need to enter the ceiling space.

## Efficacy

With performance as high as 138 LPW and a lifetime of 70,000 hours<sup>2</sup>, you may reduce your payback period for energy savings and also qualify for rebates.

## Dimming

Reduce energy consumption and costs further with 0-10V and Mark 10 dimming. Mark 10 dimming adds dimming over line voltage without time-consuming and costly wiring.



## Eco-friendly

In addition to the stylish, modern aesthetics, EvoKit helps to support sustainability goals and mandates with LED's long life and energy savings, and reduction in scrap materials compared to a complete replacement.

## Easy to Install

See installation guide on [www.philips.com/evokit](http://www.philips.com/evokit).

\* Minimum 3-inch depth

## Ordering info

Product Number	12NC	Description	Watts <sup>3</sup>	Volts	Lumen Maintenance (Hrs.) <sup>2</sup>	Approx. Lumens <sup>3</sup>	Color Temp. (K)	Efficacy	Diffusor
<b>Dimming: 0-10V</b>									
515692	929000781813	EvoKit 2x2 P 23L 17W 835 2 0-10 7 G4	17	120-277	70,000	2300	3500	134	Ribbed
515759	929000782213	EvoKit 2x2 P 23L 17W 840 2 0-10 7 G4	17	120-277	70,000	2300	4000	137	Ribbed
◆ 516005	929000783313	EvoKit 2x2 P 32L 24W 835 2 0-10 7 G4	24	120-277	70,000	3200	3500	132	Ribbed
◆ 515940	929000782713	EvoKit 2x2 P 32L 24W 840 2 0-10 7 G4	24	120-277	70,000	3200	4000	135	Ribbed
516237	929000785513	EvoKit 2x4 P 30L 22W 835 2 0-10 7 G4	22	120-277	70,000	3000	3500	135	Ribbed
516039	929000783613	EvoKit 2x4 P 30L 22W 840 2 0-10 7 G4	22	120-277	70,000	3000	4000	137	Ribbed
◆ 516286	929000786013	EvoKit 2x4 P 36L 27W 835 2 0-10 7 G4	27	120-277	70,000	3600	3500	135	Ribbed
◆ 516328	929000786413	EvoKit 2x4 P 36L 26W 840 2 0-10 7 G4	26	120-277	70,000	3600	4000	137	Ribbed
◆ 516427	929000787413	EvoKit 2x4 P 42L 32W 835 2 0-10 7 G4	32	120-277	70,000	4200	3500	134	Ribbed
◆ 516369	929000786813	EvoKit 2x4 P 42L 31W 840 2 0-10 7 G4	31	120-277	70,000	4200	4000	136	Ribbed
516534	929000788513	EvoKit 2x4 P 47L 36W 835 2 0-10 7 G4	36	120-277	70,000	4700	3500	132	Ribbed
516476	929000787913	EvoKit 2x4 P 47L 35W 840 2 0-10 7 G4	35	120-277	70,000	4700	4000	135	Ribbed
517482	929000798813	EvoKit 2x2 P 32L 24W 835 2 0-10 7 G4 SM	24	120-277	70,000	3200	3500	132	Smooth
517466	929000798613	EvoKit 2x2 P 32L 24W 840 2 0-10 7 G4 SM	24	120-277	70,000	3200	4000	135	Smooth
517508	929000799013	EvoKit 2x4 P 36L 27W 835 2 0-10 7 G4 SM	27	120-277	70,000	3600	3500	135	Smooth
517516	929000799113	EvoKit 2x4 P 36L 26W 840 2 0-10 7 G4 SM	26	120-277	70,000	3600	4000	137	Smooth
517540	929000799413	EvoKit 2x4 P 42L 32W 835 2 0-10 7 G4 SM	32	120-277	70,000	4200	3500	134	Smooth
517524	929000799213	EvoKit 2x4 P 42L 31W 840 2 0-10 7 G4 SM	31	120-277	70,000	4200	4000	136	Smooth
<b>Dimming: SR</b>									
516013	929000783413	EvoKit 2x2 P 32L 25W 835 2 SR 7 G4	25	120-277	70,000	3200	3500	129	Ribbed
515957	929000782813	EvoKit 2x2 P 32L 24W 840 2 SR 7 G4	24	120-277	70,000	3200	4000	132	Ribbed
516245	929000785613	EvoKit 2x4 P 30L 23W 835 2 SR 7 G4	23	120-277	70,000	3000	3500	131	Ribbed
516203	929000785213	EvoKit 2x4 P 30L 23W 840 2 SR 7 G4	23	120-277	70,000	3000	4000	133	Ribbed
516435	929000787513	EvoKit 2x4 P 42L 32W 835 2 SR 7 G4	32	120-277	70,000	4200	3500	132	Ribbed
516377	929000786913	EvoKit 2x4 P 42L 32W 840 2 SR 7 G4	32	120-277	70,000	4200	4000	134	Ribbed
516542	929000788613	EvoKit 2x4 P 47L 36W 835 2 SR 7 G4	36	120-277	70,000	4700	3500	130	Ribbed
516484	929000788013	EvoKit 2x4 P 47L 36W 840 2 SR 7 G4	36	120-277	70,000	4700	4000	132	Ribbed
517557	929000799513	EvoKit 2x4 P 42L 32W 835 2 SR 7 G4 SM	32	120-277	70,000	4200	3500	132	Smooth
517532	929000799313	EvoKit 2x4 P 42L 32W 840 2 SR 7 G4 SM	32	120-277	70,000	4200	4000	134	Smooth
517490	929000798913	EvoKit 2x2 P 32L 25W 835 2 SR 7 G4 SM	25	120-277	70,000	3200	3500	129	Smooth
517474	929000798713	EvoKit 2x2 P 32L 24W 840 2 SR 7 G4 SM	24	120-277	70,000	3200	4000	132	Smooth

See footnotes on page 11.

## SpaceWise ordering info

Model	Initial Lumens	Input Power Max Output (W)	Input Power Background Output (W)
<b>EvoKit</b>			
EvoKit 2x2 P 32L 28W 840 2 0-10 7 G3 (506766)	3200	28	–
EvoKit 2x4 P 42L 36W 840 2 0-10 7 G3 (507038)	4200	36	–
<b>EvoKit 2x2 with Spacewise (SWZ)</b>			
High Power Setting (120/277V)	3200	28	9
Medium Power Setting (120/277V)	2816	25	8
Low Power Setting (120/277V)	2464	22	7
Minimum Power Setting (120/277V)	2112	18	6
<b>EvoKit 2x4 with Spacewise (SWZ)</b>			
High Power Setting (120/277V)	4200	36	12
Medium Power Setting (120/277V)	3696	32	11
Low Power Setting (120/277V)	3234	28	10
Minimum Power Setting (120/277V)	2772	24	8
<b>Prod. No.   12NC   Description</b>			
503599	929000725913	EvoKit 2x2 SpaceWise Accessory	
503615	929000726013	EvoKit 2x4 SpaceWise Accessory	
504449	913700359103	Spacewise Programming Tool	
455436	913700364403	Switch/Dimmer	
455428	913700364203	4 position scene selector	

## Specifications/ordering info

Instantly transform your space with elegance and energy efficiency by incorporating Philips EvoKit LED retrofit kits.

**Contact your local Philips sales representative to schedule a personalized demonstration or visit [www.philips.com/evokit](http://www.philips.com/evokit) for more information**

### FOOTNOTES:

- 1) Minimum 3-inch depth.
  - 2)  $L_{70}$  72,000 hours @ 35°C based on TM21 and LM80.
  - 3) Based on photometric testing consistent with IES LM-79.
- \*\* These products do not meet DLC criteria.
- † DLC requires the product to meet specific performance requirements regarding: lumen output, spacing criteria, lumens per watt, color temperature, CRI, lifetime and warranty.
- ◆ Made to Stock product (Contact your Philips Sales Representative for stock availability and lead time. MTS products may initially be MTO).

