











40W Lighting Transformer

Indoor & Outdoor AC Magnetic Class 2 Lighting Transformer

Product Code: M40L24-AR


Magnitude's M40L24-AR is the most compact lighting transformer on the market with a magnetic transformer core. It is equipped with two auto-reset breakers, one on the input and one on the output, which protect both the load and transformer. The transformer is encased in a coated metal box that includes 2 knock-outs, one on each side, to enable easy installation that complies with electrical code requirements.


Features


Dimmable with any standard MLVTRIAC dimmer Two auto-reset circuit breakers ETL listed Certified to CSA Standard Class 2 Commercial and Residential Use

Nema 3R enclosure

Wiring compartment with 2 knock-outs for clean and easy installation.







Specifications

Max Load	40W
Input Voltage	120V AC
Input Current Full Load	0.35 A
Output Voltage Full Load	23V AC
Max Output Current Full Load	1.6A
Open Circuit Output Voltage	25V AC
Efficiency on I	88.6%
Coil Former	Double Section Bobbin
Max. Ambient Temperature	-30°C to 50°C
Min. Installation Space Between Drivers	5"Inch
Thermal Class	B130°C
Leads Primary	PVC 600V #20
Leads Secondary	PVC 300V #16
Circuit Breaker	primary and secondary auto reset
Dimensions L*W*H	5.6 in. x 2 in. x 2.14 in. (142.2mm x 50.8 mm x 54.3 mm)
Weight	35 Oz.

The specifications are subject to change without notice